



Specifications

SpeedFusion Engine	
WAN Interface	1x FE 1 or 2x Embedded LTE Modems
LAN Interface	1x FE 1x USB Port
USB LAN Port	Micro-USB B
Router Throughput	100Mbps
Recommended Users	1-60
LTE Modem	Downlink/Uplink Datarate: 100Mbps/50Mbps
LTE-A Modem	Downlink/Uplink Datarate: 300Mbps/50Mbps
Cellular and GPS Antenna Connector	4x MMCX Antenna Connectors 1x MMCX GPS Antenna Connector
Power Input	Terminal Block 12V-24V DC
Power Consumption	15W (max.)
Dimensions	2.95 x 3.25 x 1.65 inches 75 x 83 x 42 mm
Weight	0.77 pound 350 grams
Operating Temperature	-40° – 149°F -40° – 65°C
Humidity	15% – 95% (non-condensing)
Certifications	FCC, CE, RoHS, E-Mark EN 61373: 2010 - Shock and Vibration Resistance EN 50155: 2007 - Railway Applications - Electronic Equipment used on Rolling Stock
Warranty	1-Year Limited Warranty
Package Content	SpeedFusion Engine, Terminal Block, 1x Ear Mount Set (ACW-769)



SpeedFusion Engine

Integrate SpeedFusion SD-WAN Into Any System



You have a product that needs to get connected anytime, anywhere. The best solution is to integrate unbreakable connectivity into your product. The SpeedFusion Engine helps you integrate SpeedFusion SD-WAN into your product, overcoming several key challenges:

Ordering Information

	Product Code	Carrier/Region	Modems	Cellular Standard	4G Bands/Frequencies (MHz)	3G Bands/Frequencies (MHz)
LTE	SFE-DUO-LTE-US-ET	US/Americas/CAT-3	2	LTE	B2, B4, B5, B13, B17, B25	WCDMA/HSPA+/DC-HSPA+: B1, B2, B4, B5, B8 EV-DO Rev.A: BC0, BC1, BC10
	SFE-LTE-E-ET	Europe/International/CAT-4	1	LTE	B1, B3, B5, B7, B8, B20, B38 (TDD), B40 (TDD), B41 (TDD)	WCDMA/HSPA+/DC-HSPA+: B1, B5, B8
	SFE-DUO-LTE-E-ET	Europe/International/CAT-4	2	LTE	B1, B3, B5, B7, B8, B20, B38 (TDD), B40 (TDD), B41 (TDD)	WCDMA/HSPA+/DC-HSPA+: B1, B5, B8
LTEA	SFE-DUO-LTEA-W-ET	Worldwide/CAT-6	2	LTE Advanced	B1, B2, B3, B4, B5, B7, B8, B12, B13, B20, B25, B26, B29, B30, B41	WCDMA/HSPA+/DC-HSPA+: B1, B2, B3, B4, B5, B8
	SFE-DUO-LTEA-P-ET	Asia Pacific/CAT-6	2	LTE Advanced	B1, B3, B5, B7, B8, B18, B19, B21, B28, B38, B39, B40, B41	WCDMA/HSPA+/DC-HSPA+: B1, B5, B8, B9, B19 UMTS: B6 TD-SCDMA: B39

Accessories

Product Code	Description
SIM-BK8-4E-56V	SIM Injector, 8x SIM cards capacity, 4x 10/100/1000 LAN ports, 56V DC


Need to Minimize Footprint and Weight



Ultra-Compact SpeedFusion SD-WAN

The SpeedFusion Engine fits in the palm of your hand, making it easy to integrate into your existing products.


Cellular Coverage and Network Stability Not Guaranteed



Combine the Bandwidth of 2 Cellular Connections

With a Peplink router at HQ, SpeedFusion SD-WAN technology combines 2 cellular connections to ensure reliable connectivity, no matter where you deploy.

Integrating Cellular Connectivity is Complex



Plug-n-Play Integration, Low Power Consumption

With an Ethernet port, a USB port, and 10W consumption, the SpeedFusion Engine can integrate with your devices - without complicated software porting.