



127 172

10

-

BLILLE W

Zero-Variable Wireless Infrastrucure Deployment

Models: BM2HP, BM5HP

Completely integrated Radio

Directly plugs into any Antenna that has a Type N female connector

Robust Weatherproof Design

Overview

Revolutionary Design

Bullet M is the latest version of the popular Ubiquiti Bullet. Like its predecessor, Bullet M is a wireless radio with an integrated Type N RF connector that can be directly plugged in to any Antenna* to create a powerful and robust outdoor Access Point, Client, or Bridge.

The Bullet M features a signal strength LED meter for antenna alignment, a low-loss integrated N-type RF connector, and a robust weatherproof design.

With up to 600mW of power and enhanced receiver design, the Bullet M is ideal for long-distance links, capable of 100Mbps+ real TCP/IP speeds over multi-km distances.



Zero Variable Deployment

Bullet M eliminates the need to use RF cables and requires no special antenna or tools to install. No radio card / host board issues. No RF cable quality concerns. No mechanical stability concerns. No enclosure mounting requirements. With the Bullet M, operators can just plug and go.

Integrated AirMax Technology

The Bullet M can instantly become a powerful TDMA BaseStation utilizing Ubiquiti's breakthrough AirMax technology. With AirMax, PtMP networks can scale gracefully while maintaing high throughput and low latency performance.

Usage Example





Sector Antennas, Omni Antennas, Dish Antennas, etc.; any Antenna* can easily be transformed into a powerful and robust outdoor Access Point, Client, or Bridge by simply plugging in Bullet M.

 * Bullet M HP works with any antenna with a Type N female connector

** Ethernet cable and POE Adapter sold separately

Models





BM2HP (2.4GHz, Hi-Power, 28dBm), BM5HP (5GHz, Hi-Power, 25dBm)

Ubiquiti Networks, Inc. Copyright © 2011, All Rights Reserved

Software*

air OS

AirOS is an intuitive, versatile, highly developed Ubiquiti firmware technology. It is exceptionally intuitive and was designed to require no training to operate. Behind the user interface is a powerful firmware architecture which enables hi-performance outdoor multipoint networking.

Protocol Support

Ubiquiti Channelization

Spectral Width Adjust

ACK Auto-Timing

AAP Technology

Multi-Language Support

air View

Integrated on all Ubiquiti M products, AirView provides Advanced Spectrum Analyzer Functionality: Waterfall, waveform, and real-time spectral views allow operators to identify noise signatures and plan their networks to minimize noise interference.

Waterfall Aggregate energy over time for each frequency.

Waveform Aggregate energy collected.

Real-time Energy is shown real-time as a function of frequency.

Recording Automize AirView to record and report results.

air Control

AirControl is a powerful and intuitive web based server network management application which allows operators to centrally manage entire networks of Ubiqutii devices.

Network Map

Monitor Device Status

Mass Firmware Upgrade

Web UI Access

Manage Groups of Devices

Task Scheduling







Specifications

System Information					
Processor Specs	Atheros MIPS 24KC, 400MHz				
Memory Information	32MB SDRAM, 8MB Flash				
Networking Interface	1 X 10/100 BASE-TX (Cat. 5, RJ-45) Ethernet				

Wireless Approvals	FCC Part 15.247, IC RS210, CE				
RoHS Compliance	YES				

Physical / Electrical / Environmental					
Integrated N-type Male Jack (connects directly to antenna)					
15.2 x 3.7 x 3.1 cm (length, width, height)					
0.18kg					
Outdoor UV Stabilized Plastic					
Up to 24V					
Passive Power over Ethernet (pairs 4, 5+; 7, 8 return)*					
-40C to 80C					
5 to 95% Condensing					
ETSI300-019-1.4					
M2	M5				
7 Watts	6 Watts				
	Integrated N-type Male Jack 15.2 x 3.7 x 3.1 cm (0.1 Outdoor UV Sta Up to Passive Power over Etherno -40C f 5 to 95% (ETSI300 M2				

Range Performance					
Outdoor (Antenna Dependent)	Over 50km				

Specifications (cont.)

		Bu	llet M2 HP - Ope	Frequency 2412-2462 I	MHz			
			OUT	OWER: 28 dBm				
	2.4 GHz TX POWER SPECIFICATIONS				2.4 GHz RX POWER SPECIFICATIONS			
	DataRate	Avg. TX	Tolerance		DataRate	Avg. TX	Tolerance	
	6-24 Mbps	28 dBm	+/- 2 dB		24 Mbps	-83 dBm	+/- 2 dB	
1b/g	36 Mbps	25 dBm	+/- 2 dB	1b/g	36 Mbps	-80 dBm	+/- 2 dB	
110	48 Mbps	24 dBm	+/- 2 dB	110	48 Mbps	-77 dBm	+/- 2 dB	
•	54 Mbps	23 dBm	+/- 2 dB		54 Mbps	-75 dBm	+/- 2 dB	
	MCS0	28 dBm	+/- 2 dB		MCSO	-96 dBm	+/- 2 dB	
	MCS1	28 dBm	+/- 2 dB		MCS1	-95 dBm	+/- 2 dB	
	MCS2	28 dBm	+/- 2 dB		MCS2	-92 dBm	+/- 2 dB	
⊆	MCS3	28 dBm	+/- 2 dB	_	MCS3	-90 dBm	+/- 2 dB	
11n	MCS4	27 dBm	+/- 2 dB	<u>-</u>	MCS4	-86 dBm	+/- 2 dB	
	MCS5	25 dBm	+/- 2 dB		MCS5	-83 dBm	+/- 2 dB	
	MCS6	23 dBm	+/- 2 dB		MCS6	-77 dBm	+/- 2 dB	
	MCS7	22 dBm	+/- 2 dB		MCS7	-74 dBm	+/- 2 dB	

		Bul	let M5 HP - Ope	g Frequency 5170-5825 N	1Hz*			
			OUT	POWER: 25 dBm				
	5 GHz TX POWER SPECIFICATIONS				5 GHz RX POWER SPECIFICATIONS			
	DataRate	Avg. TX	Tolerance		DataRate	Avg. TX	Tolerance	
	1-24 Mbps	25 dBm	+/- 2 dB		24 Mbps	-83 dBm	+/- 2 dB	
ອ	36 Mbps	23 dBm	+/- 2 dB	b	36 Mbps	-80 dBm	+/- 2 dB	
	48 Mbps	21 dBm	+/- 2 dB		48 Mbps	-77 dBm	+/- 2 dB	
	54 Mbps	20 dBm	+/- 2 dB		54 Mbps	-75 dBm	+/- 2 dB	
	MCS0	25 dBm	+/- 2 dB		MCSO	-96 dBm	+/- 2 dB	
	MCS1	25 dBm	+/- 2 dB		MCS1	-95 dBm	+/- 2 dB	
ах	MCS2	25 dBm	+/- 2 dB	×	MCS2	-92 dBm	+/- 2 dB	
AirMax	MCS3	25 dBm	+/- 2 dB	AirMax	MCS3	-90 dBm	+/- 2 dB	
	MCS4	24 dBm	+/- 2 dB	Air	MCS4	-86 dBm	+/- 2 dB	
<u>-</u>	MCS5	22 dBm	+/- 2 dB	/ u	MCS5	-83 dBm	+/- 2 dB	
-	MCS6	20 dBm	+/- 2 dB	÷	MCS6	-77 dBm	+/- 2 dB	
	MCS7	19 dBm	+/- 2 dB		MCS7	-74 dBm	+/- 2 dB	

* Only 5725 - 5850 MHz is supported in the USA

Misc

TOUGHCable

Protect your networks from the most brutal environments with Ubiquiti's industrialgrade shielded ethernet cable, TOUGHCable.

Increase Performance Dramatically improve your ethernet link states, speeds, and overall performance with Ubiquiti TOUGHCables.

Extreme Weatherproof TOUGHCables have been built to perform even in the harshest weather and environments.

Eliminate ESD Attacks Protect your networks from devastating ESD Attacks, TOUGHCables eliminate ESD attacks and ethernet hardware damage.

Extended Cable Support TOUGHCables have been developed to have increased power handling performance for extended cable run lengths.

Bulletproof your networks

TOUGHCable is currently available in two versions: Level 1 Shielding Protection and Level 2 Shielding Protection.

Level 1 is a Category 5e (Up to 1Gbps Ethernet Support) Outdoor Carrier Class Shielded Cable.

Level 2 is a Category 5e Enhanced Gigabit Performance (1Gbps Ethernet Support) Outdoor Carrier Class Shielded Cable.

Additional Information:

- 24 AWG copper conductor pairs
- ESD Drain Wire: 26 AWG integrated ESD Drain wire to prevent ESD attacks & damage.
- · PVC outdoor rated jacket
- 0.35um foil shield
- Multi-Layered Shielding
- 1000ft (304.8m) length

Learn more: www.ubnt.com/toughcable



ESD Attacks are overwhelmingly the leading cause for device failures. The diagram below illustrates the areas vulnerable to ESD Attacks in a defenseless network. By using a grounded Ubiquiti POE adapter (sold separately) along with Ubiquiti TOUGHCable (sold separately), you can effectively eliminate ESD Attacks.





07



TERMS OF USE: The Ubiquiti radio device must be professionally installed. Shielded ethernet cable and earth grounding must be used as conditions of product warranty. It is the installers responsibility to follow local country regulations including operation within legal frequency channels, output power, and Dynamic Frequency Selection (DFS) requirements.

For further information, please visit www.ubnt.com.

All specifications in this document are subject to change without notice.

BM-DS-041411