

NanoBeam[®] ac

High-Performance airMAX[®] ac Bridge Model: NBE-5AC-19

Uniform Beamwidth Maximizes Noise Immunity

Innovative Mechanical Design

High-Speed Processor for Superior Performance



Overview

Ubiquiti Networks launches the latest generation of airMAX[®] CPE (Customer Premises Equipment), the NanoBeam[®] ac.

Improved Noise Immunity

The NanoBeam ac directs RF energy in a tighter beamwidth. With the focus in one direction, the NanoBeam ac blocks or spatially filters out noise, so noise immunity is improved. This feature is especially important in an area crowded with other RF signals of the same or similar frequency.

Integrated Design

The radio and antenna are combined to create a more efficient and compact CPE. The NanoBeam ac gets maximum gain out of the smallest footprint.

Providing high performance and an innovative form factor, the NanoBeam ac is versatile and cost-effective to deploy.

Software airOS°7

Sporting an all-new design for improved usability, airOS® v7 is the revolutionary operating system for Ubiquiti® airMAX ac products.

Powerful Wireless Features

- airMAX ac Protocol Support
- Long-Range Point-to-Point (PtP) Link Mode
- Selectable Channel Width
 - PtP: 10/20/30/40/50/60/80 MHz
 - PtMP: 10/20/30/40 MHz
- Automatic Channel Selection
- Transmit Power Control: Automatic/Manual
- Automatic Distance Selection (ACK Timing)
- Strongest WPA2 Security

Usability Enhancements

- Dynamic Configuration Changes
- Instant Input Validation
- HTML5 Technology
- Optimization for Mobile Devices
- Detailed Device Statistics
- Comprehensive Array of Diagnostic Tools, including Ethernet Cabling Test, RF Diagnostics, and airView[®] Spectrum Analyzer

Application Examples

PtMP Client Links



The NanoBeam ac used as a CPE device for each client in an airMAX PtMP network.

Wireless Client

PtP Link



The NanoBeam ac as a powerful wireless client.



Use a NanoBeam ac on each side of a PtP link.



Datasheet

Advanced RF Analytics

airMAX ac devices feature a multi-radio architecture to power a revolutionary RF analytics engine.

An independent processor on the PCBA powers a second, dedicated radio, which persistently analyzes the full 5 GHz spectrum and every received symbol to provide you with the most advanced RF analytics in the industry.

Data from the spectrum analysis and RF performance monitoring is displayed on the *Main* tab and airView Spectrum Analyzer of airOS V7.

Real-Time Reporting

The *Main* tab displays the following RF information:

- Persistent RF Error Vector Magnitude (EVM) constellation diagrams
- Carrier to Interference-plus-Noise Ratio (CINR) histograms
- Signal-to-Noise Ratio (SNR) time series plots

Spectral Analysis

airView allows you to identify noise signatures and plan your networks to minimize noise interference. airView performs the following functions:

- Constantly monitors environmental noise
- Collects energy data points in real-time spectral views
- Helps optimize channel selection, network design, and wireless performance

airView runs in the background without disabling the wireless link, so there is no disruption to the network.

In airView, there are three spectral views, each of which represents different data.

- Waterfall Aggregate energy collected for each frequency
- Waveform Aggregate energy collected
- Ambient Noise Level Background noise energy shown as a function of frequency

Available with a firmware upgrade to airOS v7.1, airView provides powerful spectrum analyzer functionality, eliminating the need to rent or purchase additional equipment for conducting site surveys.

Multi-Radio Architecture



Constellation Diagrams and CINR Histograms



SNR Time Series Plots



Dedicated Spectral Analysis



airCRM

Powerfully scale your business with airCRM™, a suite of WISP applications that help you manage your business. To sign up for the public beta, visit: aircrm.ubnt.com

air CRM Control

Provision, monitor, and manage all devices from a central interface. Enjoy quicker deployments, healthier networks, and faster customer service response times.

Use airCRM Control to perform the following tasks:

- Upgrade firmware
- Manage passwords
- Monitor and analyze network traffic
- Manage devices

air CRM Billing

A streamlined billing and customer management solution delivers automated invoicing, payment reminders, and credit card processing with Authorize.Net.

Use airCRM Billing to perform the following tasks:

- Create invoices
- Manage accounts
- Enable a customer portal
- · Generate detailed reports

	FIL	FILTER BY: Q AP STATION					West Office 9. Configure					
(}-0		DEVICE NAME	CAPACITY		IP ADDRESS SSID		MODE FREQUENCY		PRODUCT NAME: NanoStation Loco M5 LOGICAL TYPE: AP			
Г	0	Napa			192.168.1.30	UW_11	Station	5315 MHz				
	•	Campus Cafe	_	2.45 Mbps	192.168.1.2	UW_11	Station	5315 MHz		CLIENTS	STATS	
	•	Campus West		5.68 Mbps	192.168.1.45	UW_11	Station	5315 MHz		Past 24 hours	iours/Top 20 clients 😢	
	•	Claremont		7 Mbps	192.168.1.125	UW_11	Station	5315 MHz	EFFICIENCY	_		
	•	Denali Bend		65.68 Mbps (6)	192.168.1.48	Mezzo_EN2	Access Point	2429 MHz	5115		-	
	•	Escarpa		15 Mbps	192.168.1.11	UW_11	Station	5315 MHz	CUENT 1	AIRTIM	SIGNAL	CAPACITY
	•	Glass House		15.25 Mbps	192.168.1.25	UW_11	Station	5315 MHz		AIRTIME		
	•	KANET-C1		20 Mbps	192.168.1.98	Mezzo_EN2	Station	2429 MHz	 192.168.1.12 NanoStation M5 	2%	-61	15 Mbps
	•	KANET-C2		17.34 Mbps	192.168.1.101	Mezzo_EN2	Station	2429 MHz	• 192.168.1.13	1%	-61	5.68 Mbp
	•	Lakeview Terrace		53.82 Mbps (10)	192.168.1.88	UW_11	Access Point	5315 MHz	1649 Ave. 54			
	٠	Marigold Mt.		18.23 Mbps	192.168.1.32	UW_11	Station	5315 MHz	• 192.168.1.14 1821 Atherton	3%	-61	7 Mbps
	٠	Millbridge		40 Mbps	192.168.1.21	UW_11	Station	5315 MHz	• 192.168.1.15	5%	-61	17.34 Mt
	٠	North Pacific		18.67 Mbps	192.168.1.22	UW_11	Station	5315 MHz	18 McKinley			
	٠	NanoStation M5		84 Mbps (3)	192.168.1.73	WMTC_Primary	Access Point	5840 MHz	 192.168.1.16 44 Boyd 	7%	-61	40 Mbps
	٠	NanoStation M2		19.85 Mbps	192.168.1.72	Mezzo_EN2	Station	2429 MHz	• 192.168.1.17	13%	-61	18.67 Mb
	٠	North Pacific		50 Mbps	192.168.1.51	UW_11	Station	5315 MHz	Rocket M5			
	٠	Ridgeview		32.33 Mbps	192.168.1.61	WMTC_Primary	Station	5840 MHz	 192.168.1.16 Bellvue 			
	٠	Stratford		38.75 Mbps	192.168.1.17	WMTC_Primary	Station	5840 MHz	• 192.168.1.19	1%	-61	38.75 Mt
	٠	Talmadge		39.99 Mbps	192.168.1.27	Mezzo_EN2	Station	2429 MHz	Windham High	4%	-61	
	٠	Verdugo		43.12 Mbps	192.168.1.81	Mezzo_EN2	Station	2429 MHz	• 192.168.1.20 ISB	4%	-61	43.12 Mb
	٠	West Lorry		59.12 Mbps	192.168.1.109	WMTC_Primary	Station	5840 MHz	• 192.168.1.21	5%	-61	59.12 Mb
	•	Westfork		55 Mbps	192.168.1.15	Mezzo EN2	Station	2429 MHz	NanoStation M5			



Datasheet

Technology airMAX®

Unlike standard Wi-Fi protocol, Ubiquiti's Time Division Multiple Access (TDMA) airMAX protocol allows each client to send and receive data using pre-designated time slots scheduled by an intelligent AP controller.

This time slot method eliminates hidden node collisions and maximizes airtime efficiency, so airMAX technology provides performance improvements in latency, noise immunity, scalability, and throughput compared to other outdoor systems in its class.

Intelligent QoS Priority assigned to voice/video for seamless streaming.

Scalability High capacity and scalability.

Long Distance Capable of high-speed, carrier-class links.

Superior Performance

The next-generation airMAX ac technology boosts the advantages of our proprietary TDMA protocol.

Ubiquiti's airMAX engine with custom IC dramatically improves TDMA latency and network scalability. The custom silicon provides hardware acceleration capabilities to the airMAX scheduler, to support the high data rates and dense modulation used in airMAX ac technology.

Throughput Breakthrough

airMAX ac supports high data rates, which require dense modulation: 256QAM – a significant increase from 64QAM, which is used in airMAX.

With their use of proprietary airMAX ac technology, airMAX ac products supports up to 450+ Mbps real TCP/IP throughput – up to triple the throughput of standard airMAX products.



Up to 100 airMAX ac stations can be connected to an airMAX ac Sector, four airMAX ac stations are shown to illustrate the general concept.

airMAX Network Scalability



Superior Throughput Performance



Hardware Overview

Innovative Mechanical Design

- **All-in-one design** The NanoBeam ac provides both the radio and antenna in the smallest possible footprint.
- Quick and easy installation No fasteners are required for pole-mounting, and a single wall fastener (not included) is required for wall-mounting.
- **Convenient alignment** The NanoBeam ac pivots on its ball joint for easy aiming.

Compact Form Factor

- Efficient footprint The radio and antenna are combined into a single body that takes up minimal space.
- **Versatile mounting** The NanoBeam ac can be mounted in almost any position needed for line of sight.
- Aesthetics The NanoBeam ac is small enough to blend discreetly into the background at a customer's location.



NBE-5AC-19 with Mounting Hardware

Models

Using airMAX ac technology, the NanoBeam ac supports up to 450+ Mbps real TCP/IP throughput. The NanoBeam ac launches with PtP functionality, and a client mode feature will be added with a future firmware upgrade.



NanoBeam^{ee}

Specifications

NBE-5AC-19 System and Regulatory/Compliance						
Processor Specs	Atheros MIPS 74Kc, 720 MHz					
Memory	128 MB DDR2, 8 MB Flash					
Networking Interface	(1) 10/100/1000 Ethernet Port					
Wireless Approvals	FCC, IC, CE					
RoHS Compliance	Yes					

NBE-5AC-19 Physical/Electrical/Environmental						
Dimensions	189 x 189 x 125 mm (7.44 x 7.44 x 4.92 in)					
Weight	0.530 kg (1.17 lb)					
Power Supply	24V, 0.5A Gigabit PoE					
Power Method	Passive PoE (Pairs 4, 5+; 7, 8 Return)					
Supported Voltage Range	20-26VDC					
Max. Power Consumption	8W					
Gain	19 dBi					
Operating Frequency Worldwide USA	5150 - 5875 MHz 5725 - 5850 MHz					
Wind Loading	45.4 N @ 200 km/h (10.2 lbf @ 125 mph)					
Wind Survivability	200 km/h (125 mph)					
LEDs	(1) Power, (1) LAN, (4) WLAN					
Signal Strength LEDs	Software-Adjustable to Correspond to Custom RSSI Levels					
Channel Sizes PtP Mode PtMP Mode	10/20/30/40/50/60/80 MHz 10/20/30/40 MHz					
Polarization	Dual Linear					
Enclosure	Outdoor UV Stabilized Plastic					
Mounting	Pole-Mount (Kit Included), Wall-Mount					
ESD/EMP Protection	Air: ± 24 kV, Contact: ± 24 kV					
Operating Temperature	-40 to 70° C (-40 to 158° F)					
Operating Humidity	5 to 95% Noncondensing					
Salt Fog Test	IEC 68-2-11 (ASTM B117), Equivalent: MIL-STD-810 G Method 509.5					
Vibration Test	IEC 68-2-6					
Temperature Shock Test	IEC 68-2-14					
UV Test	IEC 68-2-5 at 40° C (104° F), Equivalent: ETS 300 019-1-4					
Wind-Driven Rain Test	ETS 300 019-1-4, Equivalent: MIL-STD-810 G Method 506.5					

Datasheet

Specifications

		NE	3E-5AC-19 Out	put Power: 26 c	lBm			
TX Power Specifications				RX Power Specifications				
Modulation	Data Rate	Avg. TX	Tolerance	Modulation	Data Rate	Sensitivity	Tolerance	
	1x BPSK (1/2)	26 dBm	± 2 dB	airMAX ac	1x BPSK (1/2)	-96 dBm	± 2 dB	
	2x QPSK (1/2)	26 dBm	± 2 dB		2x QPSK (1/2)	-95 dBm	± 2 dB	
	2x QPSK (¾)	26 dBm	± 2 dB		2x QPSK (¾)	-92 dBm	± 2 dB	
ac	4x 16QAM (½)	26 dBm	± 2 dB		4x 16QAM (½)	-90 dBm	± 2 dB	
	4x 16QAM (¾)	26 dBm	± 2 dB		4x 16QAM (¾)	-86 dBm	± 2 dB	
airMAX	6x 64QAM (⅔)	25 dBm	± 2 dB		6x 64QAM (⅔)	-83 dBm	± 2 dB	
ai	6x 64QAM (¾)	25 dBm	± 2 dB		6x 64QAM (¾)	-77 dBm	± 2 dB	
	6x 64QAM (5%)	24 dBm	± 2 dB		6x 64QAM (5%)	-74 dBm	± 2 dB	
	8x 256QAM (¾)	22 dBm	± 2 dB		8x 256QAM (¾)	-69 dBm	±2dB	
	8x 256QAM (5%)	22 dBm	± 2 dB		8x 256QAM (5%)	-65 dBm	± 2 dB	









Horizontal Azimuth

-90



Horizontal Elevation





Specifications are subject to change. Ubiquiti products are sold with a limited warranty described at: www.ubnt.com/support/warranty ©2014-2015 Ubiquiti Networks, Inc. All rights reserved. Ubiquiti, Ubiquiti Networks, the Ubiquiti U logo, the Ubiquiti beam logo, airCRM, airMAX, airOS, airView, and NanoBeam are trademarks or registered trademarks of Ubiquiti Networks, Inc. in the United States and in other countries. All other trademarks are the property of their respective owners.

www.ubnt.com