SITE MONITORING UNIT

KEY FEATURES

- Easy-to-install in sites with similar configurations: easily configurable file upload/download
- Powerful monitoring functions: Support 4 serial ports on board, able to connect SM modules and various third-party intelligent equipment by developing protocol adaption and configuration files
- High quality failure information: Due to intelligent alarm setup through PLC use
- Quick failure analysis: storage of the most recent 400 alarms
- Convenient data analysis: Up to 600 real time data points and 10 groups of battery test log can be saved in local storage

Introduction

The EnergyMaster[®] DPU is a standalone data processing unit. It provides remote monitoring for control of energy equipment and environmental control of telecom site with its powerful functionality, facilitating easy maintenance and management of a site.

The DPU not only provides common analog/digital inputs and outputs, but also provides AC/ Diesel monitoring via SM AC, battery monitoring via SM BAT and a large number of generic I/O via SM IO. Moreover, the DPU can communicate with Emerson or 3rd party intelligent equipment via its serial port, which will improve its monitoring capabilities for intelligent equipment.

If maintenance and site visits, related to the telecom site, are based upon this information they can be optimized to save both time and money, especially if the site is located remotely.

The information and alarms, from a specific site, can be monitored or checked by means of a simple web browser or special monitoring software. When using a web browser no additional software is needed and the login to monitor the site is password protected.

The DPU is a supervision and control unit designed for global use, achieving high telecom standards, and providing great flexibility and expandability.



Energy Master DPU

Technical Specifications, Energy Master® DPU

GENERAL	
Power Supply	19 VDC to 60 VDC
Power Consumption	20 W
Operating Temperature Range	-10°C to +50°C / 14°F to 122°F
Relative Humidity	5 to 95%
EMC	EN55022: class A, FCC part 15: class A
Safety	GB4943, UL60950, EN60950
Approvals	CE and UL

MECHANICAL DATA	
Dimensions (H x W x D)	440 x 295 x 44 (mm) / 16.9 x 11.3 x 1.7 (inches), tolerance: ±1 mm
Standard Installation Methods	Mounted on wall or in 19" cabinet
Weight	< 5 kg / 11 lbs

COMMUNICATION INTERFACES AND INPUTS/OUTPUTS		
External Communication	RS232 modem, RS232 console, TCP/IP, SNMP, Web server	
4 Configurable COM Ports	COM1: RS422 / RS485 / RS232 COM2: RS422 / RS485 COM3: RS485 / RS232 COM4: RS232	
Inputs (on-board)		
1 Digital Input	Smoke sensor	
1 Digital Input	Infrared sensor	
1 Digital Input	Water detector	
1 Digital Input	Burglar sensor	
10 Analog Inputs	32 mA / 60 VDC	
¹² C Protocol Input	¹² C temperature/humidity sensor	
Outputs (on-board)		
4 Relay Outputs	1 A / 30 VDC	
+12 V Output	11.8 VDC to 13.2 VDC, 0.2 A	
+24 V Output	21.6 VDC to 26.4 VDC, 0.4 A	
USB Output (Reserved)	200 mA	

EXTENDED I/O

Up to 45 SM modules in any configuration of SM IO, SM BAT and SM AC

EXAMPLES OF ALARMS

DC power plant alarms, AC mains failure, rectifier failure, high temperature alarm, smoke alarm, water leakage alarm, and burglar alarm



Non Vertiv DC Power

ABBREVIATIONS		
DPU	Data Processing Unit	
ENEC	EnergyMaster ENEC, multiplatform, multiuser, distributed multi-language web environment for monitoring of Vertiv DC, HVAC, pumps, and UPS equipment, along with batteries and lighting	
PSEM	Power Supply and Environment Monitoring system	
PSTN	Public Switched Telephone Network, an ordinary telephone line	
SM AC	Supervision Module for Alternating Current	
SM BAT	Supervision Module for Battery Backup	
SM DU	Supervision Module for additional alarms in extension cabinets	
SM IO	Supervision Module for generic monitoring	

VertivCo.com | Vertiv Headquarters, 1050 Dearborn Drive, Columbus, OH, 43085, USA

© 2018 Vertiv Co. All rights reserved. Vertiv and the Vertiv logo are trademarks or registered trademarks of Vertiv Co. All other names and logos referred to are trade names, trademarks or registered trademarks of their respective owners. While every precaution has been taken to ensure accuracy and completeness herein, Vertiv Co. assumes no responsibility, and disclaims all liability, for damages resulting from use of this information or for any errors or omissions. Specifications are subject to change without notice.